



Before connecting your Foundation 2000RE, please take an inventory of the items in your package.

Standard Items	
Main Unit	Processing unit, containing I/O connectors and an RPE receiver.
Edit Controller	Remote controller with jog/shuttle knob, touch-sensitive screen, and dedicated transport and editing buttons.
Wrist rest	Comfort rest that attaches to the front of the Edit Controller.
Power supply	Provides power to the Edit Controller.
2 power cables	One cable connects Main Unit to power source. One cable connects Edit Controller's power supply to power source.
Edit Controller cable and clip	25' cable for connecting Edit Controller to Main Unit and power supply.
Optical cable	Cable for connecting ADAT or SPDIF digital audio to the Toslink optical connector.
Guide brackets and screws	Brackets and screws for mounting the Main Unit in a rack.
Fuse and holder	1.6A, 250V fuse that complies with European safety standards
User's Guide	Operational manual that describes recording, editing, synchronization and project management. Includes a tutorial to help you get started with your new Foundation 2000RE.
Appendix	Information about exchanging data between a Foundation 2000RE and an original Foundation 2000 (including LS/LX configurations), and descriptions of new features, such as TimeFlex™ and Event Grouping.
Registration card	Official registration of ownership. Please note the serial numbers for your records and send the registration card back to Fostex.

Optional item	
RPE™	Removable Project Environment (540 MB or 1.3 GB hard drive).

Fostex Customer Support
2 Buck Road, Suite 2, Hanover, NH 03755-2715
USA and Canada 1-800-8FOSTEX
International 1-603-643-4748